

NMEA DISTRIBUTOR

NNND-100



NNND-100 NMEA Distributor converts 1 channel NMEA to 4 channels.

- Power Supply: DC 9 V~24 V
- Rated Current: Max 150 mA@9 V
- Input: NMEA 0183, RS422, 1 port
- Output: NMEA 0183, RS422, 4ports
- Operating Environment: - 40°C~85°C

NMEA DISTRIBUTOR

NNND-200

NNND-200 is a NMEA distributor/buffer to provide 8 NMEA outputs from 4 inputs.

The baud rate can be up to 38400bps from 4800bps, while the default rate is set as 4800bps.

With a built-in optical-coupled isolator, the distributor is a reliable and professional device, which can be used on board. The external equipment connected to the distributor can be safely protected from lightning surges on line.

NNND-200 contains two NMEA buffers:

Buffer 1: 2 inputs/4 outputs. When used for GNSS buffer, all 4 NMEA outputs will keep on unless both GNSS inputs fail simultaneously. When both Input 1 and Input 2 are valid, only Input 1 will be selected as default.

Buffer 2: 2 inputs/4 outputs. Same as Buffer 1.

Buffer 1 and Buffer 2 can be combined into a new buffer with 4 inputs/8 outputs.



- Type of Interface: RS485/RS422
- Standards: Conforms to IEC 61162-1, IEC 61162-2, NMEA 0183 Standards
- Number of Inputs: 4
- Number of Outputs: 8
- Power Supply: DC 24 V, 300 mA
- LED Indicators: NMEA inputs, NMEA outputs
- Baud Rate: 4800 bps~38400 bps (default 4800 bps)
- Cable Length: 0~5 m
- Size: 35 (H) × 255 (W) × 175 (D) mm
- Operating Environment: - 45°C~85°C, relative humidity 5% to 95%